


Pioneer

Service Manual



CDJ-350

ORDER NO.
RRV4069

MULTI PLAYER

CDJ-350

THIS MANUAL IS APPLICABLE TO THE FOLLOWING MODEL(S) AND TYPE(S).

Model	Type	Power Requirement	Remarks
CDJ-350	SYXJ8	AC 220 to 240 V	
CDJ-350	CUXJ	AC 120 V	
CDJ-350	FLXJ	AC 110 V to 240 V	
CDJ-350	KXJ5	AC 220 V	
CDJ-350	AXJ5	AC 220 to 240 VV	



For details, refer to "Important Check Points for good servicing".

PIONEER CORPORATION 1-1, Shin-ogura, Saiwai-ku, Kawasaki-shi, Kanagawa 212-0031, Japan
PIONEER ELECTRONICS (USA) INC. P.O. Box 1760, Long Beach, CA 90801-1760, U.S.A.
PIONEER EUROPE NV Haven 1087, Keetberglaan 1, 9120 Melsele, Belgium
PIONEER ELECTRONICS ASIACENTRE PTE. LTD. 253 Alexandra Road, #04-01, Singapore 159936
©PIONEER CORPORATION 2010

12. PCB PARTS LIST

NOTES: ● Parts marked by “NSP” are generally unavailable because they are not in our Master Spare Parts List.
● The ⚠ mark found on some component parts indicates the importance of the safety factor of the part. Therefore, when replacing, be sure to use parts of identical designation.
● When ordering resistors, first convert resistance values into code form as shown in the following examples.
Ex.1 When there are 2 effective digits (any digit apart from 0), such as 560 ohm and 47 k ohm (tolerance is shown by J = 5%, and K = 10%).
560 Ω → 56 × 10¹ → 561.....RD1/4PU 5 6 1 J
47 kΩ → 47 × 10³ → 473.....RD1/4PU 4 7 3 J
0.5 Ω → R50.....RN2H 5 0 K
1 Ω → 1R0.....RS1P 1 R 0 K
Ex.2 When there are 3 effective digits (such as in high precision metal film resistors).
5.62 kΩ → 562 × 10¹ → 5621.....RN1/4PC 5 6 2 1 F
● Meaning of the figures and others in the parentheses in the parts list.
Example) IC 301 is on the point (face A, 91 of x-axis, and 111 of y-axis) of the corresponding PC board.
IC 301 (A, 91, 111) IC NJM2068V

Mark No. Description Part No.

LIST OF ASSEMBLIES

NSP	1..PANL ASSY	DWM2380
	2..PNLB ASSY	DWX3106
	2..JACK ASSY	DWX3107
	2..SLMB ASSY	DWX3108
	2..TCHB ASSY	DWX3109
C	2..J0GB ASSY	DWX3124
NSP	1..MAGN ASSY	DWM2391
	2..MAIN ASSY	DWX3105
	2..CNCT ASSY	DWX3111
⚠	1..SMPS ASSY (SYXJ8,FLXJ,KXJ5,AXJ5)	DWR1482
⚠	1..SMPS ASSY (CUXJ)	DWR1481

Mark No. Description Part No.

CNCT ASSY

MISCELLANEOUS

L	951,952 INDUCTOR	CTF1410
S	951 SLIDE SWITCH	VSH1018
CN951	12P FFC CONNECTOR	DKN1450
CN952	24P FFC CONNECTOR	DKN1445
CN953	5P CONNECTOR	DKN1402
CN954	CONNECTOR	DKN1407
CN955	4P CONNECTOR	DKN1288

RESISTORS

R	967,968	RS1/10SR0R0J
Other Resistors		RS1/16SS###J

CAPACITORS

C	951,955	CKSSYB104K16
C	952,953,964,968	CKSSYB103K16
C	956,969	CEVQW220M16

SLMB ASSY

MISCELLANEOUS

S	751,752 PUSH SWITCH	DSG1017
CN751	5P CONNECTOR	VKN1265

Mark No. Description Part No.

MAIN ASSY

SEMICONDUCTORS

IC	101	DYW1792
IC	102	K4S561632J-UC75
IC	103	R5S72630P200FP
IC	105	TC74VHC04FT
IC	107	TS3USB30RSW
IC	201	TC94A15FG
IC	203	NJM2903M
IC	204	BD7956FS
IC	205	TC7W04FU
⚠	IC 206	BA00BC0WFP
IC	301	DSPC56371AF180
IC	302	PCM1742KE
IC	303	RNB4580F
⚠	IC 401	BA33BC0WFP
⚠	IC 402,408	S-1170B33UC-OTS
⚠	IC 403,404	BD00KA5WFP
⚠	IC 405,406	NJM2872BF0
⚠	IC 409	BD9326EFJ
IC	410	TC74VHCT08AFTS1
IC	411	TC74VHC08FTS1
Q	101,405,408	HN1C01FU
Q	102,410,412,413	RT1N241M
Q	104,107,302,303	RT3T22M
Q	109	RT1N141M-11
Q	201	2SA1036K
Q	301,402,404,406	2SA1576A
Q	411	LSC4081UB
Q	414	RT1P141M
Q	415	2SA1576A
D	101,103,304,405	1SS352
D	401	RSX201L-30
D	406	1SS352
L	201-218 INDUCTOR	CTF1545
L	403 INDUCTOR	CTH1254
F	101,102,301 EMI FILTER	DTL1106
KN	404 WRAPPING TERMINAL	CKF1089
X	101 CRYSTAL(33 MHz)	DSS1193
X	102 CRYSTAL (48 MHz)	ASS7099

MISCELLANEOUS

L	201-218 INDUCTOR	CTF1545
L	403 INDUCTOR	CTH1254
F	101,102,301 EMI FILTER	DTL1106
KN	404 WRAPPING TERMINAL	CKF1089
X	101 CRYSTAL(33 MHz)	DSS1193
X	102 CRYSTAL (48 MHz)	ASS7099

A



65