

Pioneer *sound.vision.soul*

Service Manual



PDP-R04E

ORDER NO.
ARP3179

MEDIA RECEIVER

PDP-R04E

THIS MANUAL IS APPLICABLE TO THE FOLLOWING MODEL(S) AND TYPE(S).

Model	Type	Power Requirement	Remarks
PDP-R04E	WYVI6	AC220-240V	
PDP-R04E	WYVI6XK	AC220-240V	

Please connect this model to the PLASMA DISPLAY PDP-504PE or PDP-434PE, for adjustment and operation inspection.



For details, refer to "Important symbols for good services".

Confirm it

Serial No.

○○ WYVI6 : □□ SS ##### △△
○○ WYVI6XK : □□ UK ##### △△

PIONEER CORPORATION 4-1, Meguro 1-chome, Meguro-ku, Tokyo 153-8654, Japan
PIONEER ELECTRONICS (USA) INC. P.O. Box 1760, Long Beach, CA 90801-1760, U.S.A.
PIONEER EUROPE NV Haven 1087, Keetberglaan 1, 9120 Melsele, Belgium
PIONEER ELECTRONICS ASIACENTRE PTE. LTD. 253 Alexandra Road, #04-01, Singapore 159936
 ©PIONEER CORPORATION 2003

T-ZZK NOV. 2003 printed in Japan

1. SPECIFICATIONS

Item			Media Receiver, Model: PDP-R04E
Colour System			PAL/SECAM/NTSC 3.58/NTSC 4.43/PAL 60
TV Function	Receiving System		B/G, D/K, I, L/L'
	Tuner	VHF/UHF	E2–E69ch, F2–F10ch, I21–I69ch, IR A–IR Jch
		CATV	Hyper-band, S1–S41ch
	Auto Channel Preset		99 ch, Auto Preset, Auto Label, Auto Sort
	STEREO		NICAM/A2
Terminals	Rear	INPUT 1	SCART (AV in, RGB in, TV out)
		INPUT 2	SCART (AV in/out, S-VIDEO in, AV link* ¹)
		INPUT 3	SCART (AV in/out, S-VIDEO in, RGB in, AV link* ¹), Component Video in, HDMI in
		Antenna	75 Ω Din Type for VHF/UHF in
	Front	INPUT 4	S-VIDEO, AV in
		PC	15 Pin mini D-Sub, Audio in
MONITOR OUTPUT Terminal (Rear)			S-VIDEO out, AV out
SUB WOOFER OUTPUT Terminal (Rear)			Variable
PHONES OUTPUT Terminal (Front)			16–32 Ω recommended
Power Requirement			220–240 V AC , 50/60 Hz, 38 W (0.4 W Standby)
Dimensions			420 (W) × 90 (H) × 297 (D) mm
Weight			5.0 kg

• accessories

